

# PACSystems\* RX3i

## RX3i Genius Communications Gateway IC695GCG001-CD

GFK-2900E

November 2016

### Important Product Information

General Description	Product updated due to component obsolescence of internal serial flash memory device. Added WEEE symbol to product and to carton labels. There are no changes to product form, fit, or function.	
	Hardware ID:	IC695GCG001
	Primary Firmware:	Revision 2.0.1.0
Product Documentation	<i>PACSystems RX3i System Manual</i>	GFK-2314M
	<i>PACSystems RX3i Genius Communications Gateway Quick Start Guide</i>	GFK-2891C
	<i>PACSystems RX3i Genius Communications Gateway User Manual</i>	GFK-2892B
	<i>PACSystems IC695GCG001 Genius Communications Gateway IPI</i>	GFK-2900E

### Release History

Catalog No.	Firmware Version	Date	Description
IC695GCG001-CD	2.0.1.0	Nov 2016	Product updated due to component obsolescence of internal serial flash memory device. Added WEEE symbol.
IC695GCG001-BD	2.0.1.0	Aug 2016	Removed the unused Genius B connector and the Bus B LED.
IC695GCG001-AD	2.0.1.0	Aug 2016	Adds support for the VersaMax Genius Network Interface, the IC660BBS101 isolated I/O block, and additional Genius baud rates. Fixes a problem with input data mapping for the IC660BBD120 High-Speed Counter.
IC695GCG001-AC	1.1.1.0	Feb 2016	Changed behavior of Genius Block circuit fault.
IC695GCG001-AB	1.1.0.4	Feb 2015	Fixes output glitch issues and adds enhancement to <i>Clear All Circuit Faults</i> COMMREQ.
IC695GCG001-AA	1.0.4.14	June 2014	Initial Release.

### Firmware Updates/Upgrades

Upgrade Strategy	Units in the field are not upgradable to the C hardware revision. However, the firmware in all previous versions of IC695GCG001 is field-upgradable, using the firmware upgrade kit listed in this table. It is recommended that all devices (-AC or earlier) be upgraded in this manner.
Upgrade Kit	41G2015-MS10-000-A3.zip Firmware version 2.0.1.0

### New Features in this Release

None

### Issues Resolved in this Release

None

\* Indicates a trademark of General Electric Company and/or its subsidiaries. All other trademarks are the property of their respective owners.

**Functional Compatibility**

PLC CPU Firmware Version Requirements	CPE305/CPE310 Primary Firmware Release 8.15 or later CPU315/CPU320 Primary Firmware Release 8.15 or later CRU320 Primary Firmware Release 8.95 or later CPE330 Primary Firmware Release 8.90 or later (Other CPU models are not supported)																																																				
Programmer Version Requirements	PME 8.00 up to 8.50 (must import GSDML file) PME 8.50 SIM 3 or later (GSDML file is included in PME install)																																																				
GSDML Version Requirements	GSDML-V2.3-GE-GENIUSGateway-20160818.xml																																																				
RX3i PROFINET Controller	IC695PNC001 with firmware version 2.05 or later. Version 2.11 or later is required to use the new Clear All Circuit Faults feature introduced in Gateway version 1.1.0.4.																																																				
Genius I/O Devices	<p>The following Genius I/O devices are supported by the Genius Communications Gateway. Do not connect other types of Genius devices to networks controlled by a Genius Communications Gateway.</p> <table> <tr> <td>IC200GBI001</td> <td>VersaMax Genius Network Interface Unit</td> </tr> <tr> <td>IC660BBA020</td> <td>24/48 Vdc 4-Input/2-Output Analog Block</td> </tr> <tr> <td>IC660BBA021</td> <td>24/48 Vdc RTD Input Block</td> </tr> <tr> <td>IC660BBA023</td> <td>24/48 Vdc Thermocouple Input Block</td> </tr> <tr> <td>IC660BBA024</td> <td>24/48 Vdc Current-Source Analog Block</td> </tr> <tr> <td>IC660BBA025</td> <td>24/48 Vdc Current-Source Output Block</td> </tr> <tr> <td>IC660BBA026</td> <td>24/48 Vdc Current-Source Input Block</td> </tr> <tr> <td>IC660BBA100</td> <td>115 Vac 4-Input/2-Output Analog Block</td> </tr> <tr> <td>IC660BBA101</td> <td>115 Vac RTD Input Block</td> </tr> <tr> <td>IC660BBA103</td> <td>115 Vac/125 Vdc Thermocouple Input Block</td> </tr> <tr> <td>IC660BBA104</td> <td>115 Vac/125 Vdc Current-Source Analog Block</td> </tr> <tr> <td>IC660BBA105</td> <td>115 Vac/125 Vdc Current-Source Output Block</td> </tr> <tr> <td>IC660BBA106</td> <td>115 Vac/125 Vdc Current-Source Input Block</td> </tr> <tr> <td>IC660BBD020/022</td> <td>24/48 Vdc 16-Circuit Source I/O Blocks</td> </tr> <tr> <td>IC660BBD021/023</td> <td>24/48 Vdc 16-Circuit Sink I/O Blocks</td> </tr> <tr> <td>IC660BBD024</td> <td>12/24 Vdc 32-Circuit Source I/O Block</td> </tr> <tr> <td>IC660BBD025</td> <td>5/12/24 Vdc 32-Circuit Sink I/O Block</td> </tr> <tr> <td>IC660BBD101</td> <td>115 Vac Low-leakage 8-Circuit I/O Block</td> </tr> <tr> <td>IC660BBD110</td> <td>115 Vac 16-Circuit Input Block</td> </tr> <tr> <td>IC660BBD120</td> <td>High-Speed Counter</td> </tr> <tr> <td>IC660BBR100</td> <td>16-Circuit Normally-Closed Relay Block</td> </tr> <tr> <td>IC660BBR101</td> <td>16-Circuit Normally-Open Relay Block</td> </tr> <tr> <td>IC660BBS100/102</td> <td>115 Vac/125 Vdc Isolated I/O Blocks, with Failed Switch Diagnostics</td> </tr> <tr> <td>IC660BBS101/103</td> <td>115 Vac/125 Vdc Isolated I/O Block, without Failed Switch Diagnostics</td> </tr> <tr> <td>IC660HHM501/502</td> <td>Hand-Held Monitor</td> </tr> <tr> <td>IC697BEM733</td> <td>Series 90-70 Remote I/O Scanner</td> </tr> </table>	IC200GBI001	VersaMax Genius Network Interface Unit	IC660BBA020	24/48 Vdc 4-Input/2-Output Analog Block	IC660BBA021	24/48 Vdc RTD Input Block	IC660BBA023	24/48 Vdc Thermocouple Input Block	IC660BBA024	24/48 Vdc Current-Source Analog Block	IC660BBA025	24/48 Vdc Current-Source Output Block	IC660BBA026	24/48 Vdc Current-Source Input Block	IC660BBA100	115 Vac 4-Input/2-Output Analog Block	IC660BBA101	115 Vac RTD Input Block	IC660BBA103	115 Vac/125 Vdc Thermocouple Input Block	IC660BBA104	115 Vac/125 Vdc Current-Source Analog Block	IC660BBA105	115 Vac/125 Vdc Current-Source Output Block	IC660BBA106	115 Vac/125 Vdc Current-Source Input Block	IC660BBD020/022	24/48 Vdc 16-Circuit Source I/O Blocks	IC660BBD021/023	24/48 Vdc 16-Circuit Sink I/O Blocks	IC660BBD024	12/24 Vdc 32-Circuit Source I/O Block	IC660BBD025	5/12/24 Vdc 32-Circuit Sink I/O Block	IC660BBD101	115 Vac Low-leakage 8-Circuit I/O Block	IC660BBD110	115 Vac 16-Circuit Input Block	IC660BBD120	High-Speed Counter	IC660BBR100	16-Circuit Normally-Closed Relay Block	IC660BBR101	16-Circuit Normally-Open Relay Block	IC660BBS100/102	115 Vac/125 Vdc Isolated I/O Blocks, with Failed Switch Diagnostics	IC660BBS101/103	115 Vac/125 Vdc Isolated I/O Block, without Failed Switch Diagnostics	IC660HHM501/502	Hand-Held Monitor	IC697BEM733	Series 90-70 Remote I/O Scanner
IC200GBI001	VersaMax Genius Network Interface Unit																																																				
IC660BBA020	24/48 Vdc 4-Input/2-Output Analog Block																																																				
IC660BBA021	24/48 Vdc RTD Input Block																																																				
IC660BBA023	24/48 Vdc Thermocouple Input Block																																																				
IC660BBA024	24/48 Vdc Current-Source Analog Block																																																				
IC660BBA025	24/48 Vdc Current-Source Output Block																																																				
IC660BBA026	24/48 Vdc Current-Source Input Block																																																				
IC660BBA100	115 Vac 4-Input/2-Output Analog Block																																																				
IC660BBA101	115 Vac RTD Input Block																																																				
IC660BBA103	115 Vac/125 Vdc Thermocouple Input Block																																																				
IC660BBA104	115 Vac/125 Vdc Current-Source Analog Block																																																				
IC660BBA105	115 Vac/125 Vdc Current-Source Output Block																																																				
IC660BBA106	115 Vac/125 Vdc Current-Source Input Block																																																				
IC660BBD020/022	24/48 Vdc 16-Circuit Source I/O Blocks																																																				
IC660BBD021/023	24/48 Vdc 16-Circuit Sink I/O Blocks																																																				
IC660BBD024	12/24 Vdc 32-Circuit Source I/O Block																																																				
IC660BBD025	5/12/24 Vdc 32-Circuit Sink I/O Block																																																				
IC660BBD101	115 Vac Low-leakage 8-Circuit I/O Block																																																				
IC660BBD110	115 Vac 16-Circuit Input Block																																																				
IC660BBD120	High-Speed Counter																																																				
IC660BBR100	16-Circuit Normally-Closed Relay Block																																																				
IC660BBR101	16-Circuit Normally-Open Relay Block																																																				
IC660BBS100/102	115 Vac/125 Vdc Isolated I/O Blocks, with Failed Switch Diagnostics																																																				
IC660BBS101/103	115 Vac/125 Vdc Isolated I/O Block, without Failed Switch Diagnostics																																																				
IC660HHM501/502	Hand-Held Monitor																																																				
IC697BEM733	Series 90-70 Remote I/O Scanner																																																				
Hot-standby Redundancy	When using the Gateway in a Hot Standby redundancy system, with older versions of the CRU320 or CPE330 controllers, Genius I/O may not be scanned after a power cycle. This occurs if the primary controller is off and both the secondary Gateway and secondary controller are powered on at the same time. This problem is resolved in IC695CRU320 version 8.95 and later. It is also resolved in IC695CPE330 version 8.90 and later.																																																				
VersaMax Sub-Module Configuration	For firmware version 2.0.1.0 the full IO capacity must be configured for VersaMax modules Vmax_8_Channel_AI and Vmax_4_Channel_AO modules. With the GBC, you could configure a subset of IO (for example for the Vmax_8_Channel_AI) you could configure (for example) 5 AI. For the GCG, this is not currently possible and you must configure 8 AI.																																																				

**Restrictions and Open Issues**

Subject	Description
Late Genius device power-up	The Genius Gateway will not recognize any Genius device that is placed on the Genius bus after the Gateway's Connect LED transitions to the OFF state. All other Genius devices will perform I/O normally. If the power is cycled on the Gateway, it begins exchanging I/O with the Genius device.
Discrete I/O Fault	If a discrete Genius block is configured so that all of its points are inputs or all of its points are outputs, the PROFINET Controller Module (PNC) may report a <i>Valid Module Substitution</i> fault in the I/O Fault Table. The block will operate as expected. The fault can be safely ignored.
90-70 output flicker	In approximately 5% of cases, when the 90-70 Remote Scanner is power-cycled while the PLC is in RUN mode, the 90-70 outputs will flicker briefly (less than 1 second duration) when the Gateway restarts communications with the 90-70. In the other 95% of cases, the Gateway will send output data set to zero, for less than 1 second when the Gateway restarts communications with the 90-70.
Use of unsupported Genius devices	When an IC695GCG001 is used to control a Genius I/O network, the presence of unsupported Genius devices on the network can cause bus congestion, loss of fault messages, and other undesirable operation.
Configuration of 8- and 32-point discrete blocks	When configuring 8-point and 32-point discrete Genius blocks in Machine Edition, you must configure the block for both inputs and outputs. The Gateway does not support input-only or output-only configurations for these devices.
Recurrence of a circuit fault not shown in I/O Fault Table	If the Hand-Held Monitor is used to clear a circuit fault, and that fault reappears at a later time, no corresponding fault indication will appear in the I/O Fault Table. This situation is resolved by using the <i>Clear Circuit Fault</i> or <i>Clear All Circuit Faults</i> COMMREQs rather than using the HHM.
Hand-Held Monitor does not show the Gateway during a bus scan	When scanning the Genius bus with the Hand-Held Monitor, the scan will skip over the Gateway and not show it, even though the Gateway is operating properly.
Dual-Bus Redundancy not supported	The Gateway does not support Genius Dual-bus Redundancy. The Gateway can be used in Hot-standby Redundancy and Duplex Redundancy.

**Operational Notes**

Subject	Description
IC660BBD120 High-Speed Counter	<p>In Proficy Machine Edition (PME), when a Gateway is upgraded from an older GSDML file (prior to 2016) to the 20160818 version or later, if there are any Genius High-Speed Counter blocks in the configuration, PME displays a Conflicts List window indicating that the input references have been given new values. When this occurs, take note of the existing reference addresses and press the <b>Proceed</b> button. Then open the hardware configuration for the High-Speed Counter module. If either of the %I or %AI reference addresses were changed, change them back to their original values. This is a one-time operation per High-Speed Counter.</p>
Fault Contract Operation	<p>Firmware version 1.1.1.0 changes the behavior of the GCG when a Genius Block circuit fault occurs. In firmware versions 1.1.04 and earlier, a circuit fault would result in all I/O points on the Genius Block indicating a faulted condition. With firmware version 1.1.1.0 and later, when a circuit fault occurs on a Genius Block only the I/O point where the circuit fault occurred will be faulted.</p> <p><b><u>Fault Contact Operation with FW 1.1.1.0 and Later:</u></b></p> <p>When a circuit fault occurs on a discrete block or a channel fault occurs on an analog block, none of the block's <u>fault contacts</u> will energize. The only indicators of the presence of a circuit fault are an entry in the I/O Fault Table the Fault LED on the Gateway, and the Fault LED on the faulted Genius block itself.</p> <p>Prior to FW version 1.1.1.0 all of the fault contacts associated with the faulted Genius block would energize.</p>
Bus Address 0	<p>Genius bus address 0 is not available for configuration of Genius devices in Proficy Machine Edition (PME). The only Genius device that can be used at bus address 0 is the Hand-Held Monitor.</p>
Bus Addresses 30 and 31	<p>The Gateway can be assigned to bus addresses 30 and 31 only. Do not configure the Gateway to both addresses 30 and 31 simultaneously. Doing so will cause the Genius bus to operate in an unexpected manner.</p>
SNMP	<p>The Genius Communications Gateway supports Simple Network Management Protocol (SNMP). However, requests directed to the device must use the community name "ge".</p>



1-800-433-2682

1-434-978-5100

[www.geautomation.com](http://www.geautomation.com)